



COLLEGE OF ENGINEERING, SCIENCE & TECHNOLOGY

SCHOOL OF ELECTRICAL AND ELECTRONIC ENGINEERING.

TRADE/DIPLOMA IN ELECTRICAL ENGINEERING (ELECTRICAL)

EEE573 - ELECTRICAL POWER TRANSMISSION & DISTRIBUTION.

FINAL EXAMINATION - TRIMESTER 2 - 2018.

DAY/DATE: ETT TIME: ETT. ROOM: ETT

INSTRUCTIONS TO STUDENTS:

1. You are allowed 10 minutes **EXTRA** as reading time during which you are **NOT** to write.
2. Begin each answer on a fresh page and use both sides of the sheet.
3. Write your candidate number at the top of each attached sheet.
4. Insert all written foolscap, graph paper, drawing paper, etc. in their correct sequence and secure with a piece of string
5. Write clearly the number(s) of the question(s) attempted on the top of each sheet.
6. Answers to all questions must be written in **INK** on the Answer Sheet provided.
7. No programmable calculators are allowed.
8. Answer all questions.
9. **Total Marks = 100%**

*****#####*****

QUESTION ONE

- (a) Identify the six (6) main types of conductors used for overhead line work; outline their characteristics, and where they are used. (12 Marks)
- (b) With the aid of diagrams show any four (4) types of line supports. (8 marks)

QUESTION TWO

- (a) With the aid of diagrams outline the four (4) main types of vibrations experienced by the overhead line conductors. (12 marks)
- (b) Explain in your own words and with the aid of fully labeled diagrams how you would reduce the vibrations you have specified in Q2 (a) above. (8 marks)

QUESTION THREE

- (a) (i) Define what corona is.
(ii) Name three factors that corona is dependent on.
(iii) Describe three side effects of corona. (8 Marks)
- (b) A string of three insulators is used to suspend one conductor of a 33 kV, 3-phase line. The air capacitance between each cap/pin junction to the tower is $\frac{1}{5}$ the Capacitance of each unit. Draw the diagram and calculate the voltage across each insulator and the string efficiency. (12 Marks)

QUESTION FOUR

- (a) You have been asked by the System Engineer in your organization to carry out a fault calculation on a number of feeders; what are the points to note in order for you to carry out the task on hand. (4 Marks)
- (b) What is the precaution to be observed with CT's and what are the dangers that will happen if this precaution is not observed? (5 marks)
- (c) With the aid of diagrams explain the four most common distribution feeder systems applied nowadays. (8 marks)
- (d) Name any three (3) circuit breakers used in high voltage transmission. (3 marks)

QUESTION FIVE

- (a) What are the conditions that must be met before any two three phase transformers are connected in parallel? (3 Marks)
- (b) With the aid of a diagram explain the DY11 connection of a transformer. (5 Marks)
- (c) A 66 kV, 50 Hz, 120 km single core lead sheathed cable has a conductor of radius 250mm and lead sheath radius of 350mm. (Epsilon for lead is 3.6, Rho for copper is 1.71 micro-ohm-cm, Rho for insulation is 1.3×10^8 Mega-ohm-cm). Calculate:
- (i) Total resistance of core
 - (ii) The inductance
 - (iii) The capacitance
 - (iv) The insulation resistance
 - (v) The power loss due to the insulation resistance. (12 Marks)

THE END